

Ecolink Commander Flood Light



ECOLINK Commander Flood is an excellent solution for affordable and yet reliable LED floodlight. Range of wattage selection for general area outdoor floodlight requirements.

Benefits:

- Excellent Aesthetics
- Guaranteed luminous flux and durability.
- Energy Efficient.
- Simple and quick assembly

Product data

Optical system	
Power Range (W) ±10%	30W / 50W / 100W
Lumen output (typ.Avg) @ 4000k	1950lm / 3250lm / 6500lm
Lumen output tolerance (+/-)	±10%
CRI	70 (typical)
CCT	3000k / 6500k
SDCM	<7
Electronics	
Input Voltage and Frequency	DOB solution
Driver output (Voltage / current)	220-240v 50/60 hz
Operation per day (on/off times and working duration)	2 switch cycle per day, 12 hrs working
Safety Class (driver+system)	Class I
Power Factor (system)	>0.8
Power consumption (system)	30W / 50W / 100W (-10%, +10%)
Bracket tilte angle	150 deg
System Efficacy	65 lm/w
Surge Protection	yes, as per IEC
Mechanical	
Housing material	AL die cast
Reflector/lens material (LG)	PC
Cover material (Diffuser)	Tempered glass,
IPxx	65
IKxx	06
Mounting	U bracket
Power connection	Flying cable
Cable	150mm
Housing surface treatment	Powder painting
Color(s) (and RAL code)	Black;RAL9011
Brand	Ecolink
Packaging concept	color box



Thermal	
Operating temperature range	0deg - 40deg
Reliability	
Lifetime	Lifetime 8000 hrs (L70B50 at 25C)

Product List

12 NC	Product Description
911401888880	Ecolink FLE007 30w/865
911401888680	Ecolink FLE007 50w/830
911401888980	Ecolink FLE007 50w/865
911401888780	Ecolink FLE007 100w/830
911401889080	Ecolink FLE007 100w/865